

Drawmer



D S 2 0 1

d u a l n o i s e g a t e

ingenuity (*ˌɪndʒɪˈnjuːɪti*) *n.*, *pl.* *-ties*. **1.** inventive talent; cleverness. **2.** an ingenious device, act, etc.

The DS201 is a sophisticated dual channel noise gate incorporating a number of features pioneered by Drawmer, which are invaluable to the sound engineer, and not found on conventional noise gates.

- variable high pass and low pass filters for "frequency conscious" gating
- comprehensive envelope control, attack, hold, decay, and range
- key input for external triggering
- "key listen" facility
- extremely fast attack time, to preserve the natural attack of the sound
- balanced inputs and outputs
- stereo linkable
- can be used for "Gating" or "Ducking"
- high audio specification.

These features and its "user friendliness" have made it the "industry standard" throughout the world.

Setting up noise gates can be tedious and unrewarding. For example, when attempting to separate a signal from unwanted noise or crosstalk that is relatively high in level, spurious triggering of the gate by unwanted components within the sound can be a serious problem. This can often be experienced in the studio when recording a drum kit. If a gate is used to clean up the snare drum sound it is quite likely that the nearby hi-hats will spill into the snare drum microphone and cause the gate to open. Increasing the threshold level may cure this problem, but then there is a very real danger that any quieter snare drum beats may not cause the gate to open at all and the performance can easily be ruined.

The DRAWMER solution to this problem is the inclusion of two variable filters, one high-pass and one low-pass, which act upon the side-chain keying circuitry. By setting the output switch to key listen the user can hear the action of the filters and adjust them to reject high frequency spillage from the hi-hats. This now enables the gate to only open on the lower frequencies present in the snare drum.

Drawmer pioneered the concept of frequency conscious gating, and the Drawmer DS201 was the first noise gate to include this feature.

The very fast attack of the DS201 means that it can open in a matter of micro seconds, thus preserving the natural attack of whatever sound is being gated and the comprehensive envelope controls mean that the gain can be changed at whatever rate best suits the material being processed. With vocals for example, a fairly fast attack is needed so as not to clip the leading consonants but a slower release time will prevent the end of words being clipped off and will also fade out any noise gradually rather than cutting it off abruptly. This latter point is very important as the human ear is far more sensitive to rapidly changing noise levels than to a constant low level noise.

Another important role played by the gate is in the reshaping of existing sounds. An example of this might involve a simple sampling delay line used to store a sound to be re-triggered later and added to a mix. A gate can be used to impart a slower attack or faster decay to the sound and careful setting of the decay envelope can effectively hide any noise present at the end of the sample. When using a sampler or drum machine the gate can be considered a triggered envelope shaper, and the wide range allowed by the envelope controls make the DS201 ideal for this application.

The unit can be switched to accept a key input, which allows the gate to be triggered externally. An example of this would be to use a snare drum signal to open the gate on a separate ambient microphone to create a natural alternative to gated reverb.

Each channel can be individually switched from Gating to Ducking for 'voice over' applications or the removal of 'clicks' and 'pops'.

TECHNICAL SPECIFICATION:

Input impedance:	20Kohms balanced	Control ranges:	LF Filter 25Hz to 4KHz
Maximum input level:	+21.5 dBu		HF Filter 250Hz to 35KHz
Bandwidth:	±1dB 20Hz to 34KHz		Threshold Infinity to -54dB
Noise:	(Ref to +4dBu, gate open) -93dB (Ref to +4dBu, gate closed) -98dB		Attack 10µs to 1 sec
Headroom:	(Ref to +4dBu) +16dB		Hold 2ms to 2sec
Dynamic Range:	109dB		Decay 2ms to 4sec
Crosstalk:	-93dB	Function switches:	Range -80dB to 0dB
Key input impedance:	100K		Key Source: External/Internal, Gate/Duck,
Distortion:	0dBu +10dBu	LEDs (Gate mode):	Key Listen/Gate/Bypass, Stereo Link
100Hz	-015% -015%		Green: Gate open (Signal above threshold)
1KHz	-005% -005%		Yellow: Gate open (Visual indication of attack,
10KHz	-015% -02%		hold and decay characteristics)
Maximum output:	+20-5dBu (10K load) +20-0dBu (600ohm load)	LEDS (Duck mode):	Red: Gate closed (Signal below threshold)
Outputs:	Floating balanced		Green: Signal not attenuated
			Yellow: Hold time
			Red: Signal attenuated (according to range control)

PRESENTED BY:

Contact your DRAWMER dealer for further information



Drawmer Distribution Ltd., Charlotte Street Business Centre, Charlotte Street, Wakefield, West Yorkshire, WF1 1UH England.
 Tel. +44 (0) 1924 378669 Fax. +44 (0) 1924 290460
 sales@drawmer.co.uk
 www.drawmer.com